

# MICPAT-4

## Selective 4-zone paging station



The Apart MICPAT-4 is a sturdy active multizone-paging microphone. It has a flexible gooseneck and a high-quality directional condenser microphone.

With MICPAT-4 you can make paging calls to a maximum of four zones simultaneously. It has been designed specifically for use with the Apart ZONE4 pre-amplifier and future models. Multiple MICPAT-4 mics can be connected in parallel by using the optional RJ45SPLIT splitter.

Operating this microphone is very straightforward: select the zones you want to page by pushing buttons 1 to 4. You can select all zones at once by pushing the 'all' button.

The call button is momentary: push to talk. All the other buttons are latching. During paging the call LED will light orange, and all other microphones connected in parallel will be temporarily disabled (busy). In a multi-microphone setup, the MICPAT-4 will automatically detect if another microphone is already paging. This is indicated by an orange call LED. When paging has ended, the LED will return to green.

MICPAT-4 and ZONE4 have an easy plug-and-play installation and comfortable, intuitive use. As all Apart products, they have been designed with installer ease in mind!

## TECHNICAL SPECIFICATIONS

<b>active</b>	Yes	<b>polar pattern</b>	directional, low feedback, electret capsule
<b>buttons</b>	4 selection + Call + All Call	<b>indicator</b>	1 per button + multi color status
<b>zones</b>	4	<b>frequency range</b>	80 Hz - 20 kHz
<b>nominal output level</b>	2 V balanced	<b>rated output impedance in ohms</b>	50 balanced
<b>power type</b>	Phantom	<b>mic stem lenght in mm</b>	275
<b>connector</b>	RJ45	<b>cable lenght in m</b>	5
<b>cable type</b>	CAT5	<b>width in mm</b>	115
<b>height in mm</b>	60	<b>depth in mm</b>	162
<b>weight in gr</b>	550	<b>Net weight product (kg)</b>	0,70

MORE PICTURES



## ACCESSORIES



### **RJ45SPLIT**

RJ45 Splitter : 1input, 4 output (MICPAT-4 or ZONE4R)