

# REVAMP8250

8-channel bridgeable class D power amplifier, 8 x 250W, 4ohm



This 8-channel bridgeable power amplifier is probably the most versatile class-D amplifier in the range. Combined with a pre-amplifier or matrix the REVAMP8250 can be used to create 8 zones in mono, 4 zones in stereo, even 4 bridged mono or 2 bridged stereo systems can be created. The amplifier has an intelligent variable speed cooling fan built-in to keep the unit cool at all times.

When installing the REVAMP8250, a handy input overload LED indicator on the rear and amplifier clip indicator on the front will guarantee a fast and hassle-free installation. Due to the amount of channels, limited amplifiers are needed in your project. This will save money and space, making it the ideal choice for your install.

## TECHNICAL SPECIFICATIONS

dynamic output power 4 ohms in watts	8 x 350	RMS output power 4 ohms in watts	8 x 250
dynamic output power 8 ohms in watts	8 x 175	RMS output power 8 ohms in watts	8 x 125
dynamic output power bridged 8 ohms in watts	4 x 650	output power RMS bridged 8 ohms in watts	4 x 500
minimum impedance load per channel in ohms	4	minimum impedance load bridged per channel in ohms	8
power consumption (max) in watts	2200	19" (483 mm wide) rack mounting	yes
height- rack units (1U=44 mm) in U	2	height in mm	88
depth (build in) in mm	330	depth (incl front) in mm	338
power supply	115 - 230 VAC	power supply technology	switching mode power supply
output channels	8	line input balanced	8
line input unbalanced	8	channel separation	> 60 dB @ 1 kHz
power amp topology	class-D	applicable in 100V	no
applicable low impedance	yes	Net weight product (kg)	21.7

MORE PICTURES

